



## ASSEMBLY INSTRUCTIONS

1. Ensure the house electricity supply is off at the fuse board.
  2. If removing the existing fitting, carefully note the position of each set of cables. If there are loop in cables that are not connected to the light, these must be terminated in a separate terminal block not connected to the fitting.
  3. Use the hex key provided to undo the two screws securing the cover, then separate the cover by lifting away, **retaining the screws for later**.
  4. Undo the screws securing the main body onto the backplate, **and retain these for later**.
  5. Using the backplate as a template, mark and drill fixing holes. Ensure holes are drilled into a solid wall or other suitable mounting. Where required, push the rawl plug into the holes drilled.
  6. Fitting is supplied with patterned plates. Undo the fixing screws, then fit the required plate, and then secure these into position with the screws.
  7. Carefully make a small hole in the soft rubber seal from the back of backplate, then feed the supply cable through the seal whilst making sure this is a tight fit around the cable.
  8. Attach the backplate to the wall using suitable fixings. **Take care not to trap cable behind the backplate.**
  9. Make the electrical connections as follows,  
 Connect supply live (normally brown or red) to fitting live (marked "L") on the terminal block.  
 Connect supply neutral (normally blue or black) to fitting neutral (marked "N") on the terminal block.
- PLEASE NOTE:** NO EARTH must be connected to any part of this fitting. Residential wiring can vary, if you are unsure about the correct polarity, consult a qualified electrician. Ensure electrical connections are tight and no loose strands of wire protrude from the terminal blocks.
10. Attach the main body of the fitting over the backplate, then secure into position using the screws removed earlier, **take care not to over-tighten**.
  11. Clean the fitting from dust and finger marks, then fit the cover over the main body, then secure into position using the screws removed earlier. **Take care not to over-tighten**.
  12. Switch on the electricity supply at the fuse board.

## **SAFETY INFORMATION**

- \* We recommend any electrical wiring in an outdoor environment is carried out by a qualified electrician. All wiring must comply with the current edition of the IEE wiring regulations and any relevant Building Regulations.
  - \* If you are in any doubt consult a person competent to give advice on the installation of electrical equipment.
  - \* This fitting is Class 2 =  therefore no earth is required and should be fitted to a lighting supply protected by a 5 amp fuse or equivalent circuit breaker that is protected by a 30mA RCD.
  - \* This fitting is rated IP44 and is suitable for outdoor use when fitted in accordance with these instructions and IEE wiring regulations.
  - \* Before installation and servicing disconnect the electricity supply at the fuse board.
  - \* To avoid damage to concealed wiring during installation, establish the direction of the supply cable before drilling fixing holes.
  - \* **IMPORTANT: This LED fitting is NOT dimmable.**
  - \* The light source of this luminaire is not replaceable; when the light source reaches the end of its end of life the whole luminaire shall be replaced.
- SUITABLE FOR WALL MOUNT ONLY.**
- \* This product contains a light source(s) of energy efficiency class. 

## **GENERAL INFORMATION**

This fitting is designed for external use, it must be fitted to a DRY FINISH as any dampness in concrete, wood stain, paint and etc can damage finish.

**Do not use polish or abrasive cleaner - just a soft slightly damp cloth.**

*To register your product for an extended five-year warranty, please complete the simple form at*

**[www.darlighting.co.uk/warranty](http://www.darlighting.co.uk/warranty)**

*You'll need to fill in the details of the product, the retailer you purchased it from, and also the installer and the installation. Please also upload a clear copy of the original purchase invoice or receipt to complete this registration.*

**UK:** *där Lighting Ltd, Wildmere Road, Banbury, Oxon, OX16 3JZ*

**Ireland & EU:** *Dar Lighting Ireland Limited, Suite 108, Q House, 76 Furze Road, Sandymount Industrial Estate, Dublin 18*

**där**<sup>®</sup>  
lighting group



**IP44 LED POLYCARBONATE OUTDOOR  
WALL LIGHT**

**ASSEMBLY INSTRUCTIONS**